



SVMi-8

System Administrator Guide

System Administration functions can be accessed by calling the SVMi-8 from a touch tone phone. These administrative functions allow the system administrator to:

- 1) Edit System Prompts
- 2) Edit (add and remove) subscribers
- 3) Change the operating mode (Day, Night, etc.)

ACCESSING DTMF SYSTEM ADMINISTRATION

To access the DTMF system administration mode:

- 1) Call the SVMi-8 and from the Main Menu press the **[#]** key followed by **3 zeros**. If you are answered by a prompt to enter your password you are in a mailbox and must first press **[*]** to reach the Main Menu.
- 2) When prompted enter the administration password specified in the System Wide Parameters. You will be presented with the System Administration Menu.

1 EDIT SYSTEM PROMPTS

This allows you to create or edit system prompts.

- Call the SVMi-8, and access the System Administration Menu.
- Press **[1]** to edit system prompts.
- Follow the spoken instructions to edit system prompts.

At the very least you will probably need to create the following:

- Day Greeting = Prompt 1001
- Night Greeting = Prompt 1002

- Holiday Greeting = Prompt 1003
- Emergency (Bad Weather) Greeting = Prompt 1004

Only prompts above prompt # 1000 may be recorded using the DTMF system administration. To record prompts lower than # 1000 (system prompts) you must use the Voice Studio Administration tool.

NOTE: When a prompt has been recorded, sometimes there is some ambient noise at the front or back that needs to be trimmed. Press **[4]** and select trim mode. You may now clip small amounts of 'noise' from the front or back of the voice prompt. Repeatedly press **[1]** (or **[2]**) to trim small amounts from the front (or back) until the prompt sounds clean.

2 SUBSCRIBER ADMINISTRATION

This allows you to add and delete subscribers.

- Call the SVMi-8, and access the System Administration Menu.
- Press **[2]** for subscriber information.
- Follow the spoken instructions to create or delete subscribers.

3 MANUAL MODE SELECTION

This allows you to change the operating mode of the SVMi-8. You may select a specific mode (as long as it has been defined as a mode block) or you may select automatic scheduling. Changes to a specific mode will remain in effect until you manually change it back to automatic scheduling again. You may select a mode for each port in the system.

- Call the SVMi-8, and access the System Administration Menu.
- Press **[3]** to manually set the mode.
- Follow the spoken instructions to change the port number.
- Follow the spoken instructions to change the operating mode, according to the following list of options:

- 1 Day Mode
- 2 Night Mode
- 3 Holiday Mode
- 4 Emergency (bad weather) Mode
- 5-99 Any additional modes that you may create
- 0 Automatic scheduling - automatically follow the system Schedule table